

Сечение проводника, мм ²	Размеры, мм									Упаковка, шт.	Код	
	E	A	C	B	J	F	D	G	G1			
Используемый для крепления контактной площадки метиз - M16												
70	17,0	11,5	16,5	28	72,5	3,7	24,0	17,5	17,5	50	2I716L	
95	17,0	13,5	19,0	35	82,5	4,4	32,0	17,5	17,5	25	2L716L	
120	17,0	15,5	21,0	35	87,5	5,0	32,0	17,5	17,5	20	2M716L	
150	17,0	17,0	23,5	35	95,5	6,0	34,0	17,5	17,5	20	2N716L	
185	17,0	19,0	25,5	40	99,5	6,0	37,0	17,5	17,5	10	2O716L	
240	17,0	21,5	29,0	40	109,5	7,1	42,0	17,5	17,5	10	2P716L	
300	17,0	24,5	32,0	50	117,5	7,0	48,0	17,5	17,5	5	2Q716L	
400	17,0	27,5	38,5	70	138,5	10,4	55,0	23,5	17,5	5	2R716L	
Используемый для крепления контактной площадки метиз - M20												
120	21,0	17,0	21,0	35	90,5	4,1	32,0	20,5	21,5	20	2M721L	
150	21,0	17,0	23,5	35	98,5	6,0	34,0	20,5	21,5	20	2N721L	
185	21,0	19,0	25,5	40	102,5	6,0	40,0	20,5	21,5	10	2O721L	
240	21,0	21,5	29,0	40	112,5	6,5	45,0	20,5	21,5	10	2P721L	
300	21,0	24,5	32,0	50	120,5	7,0	48,0	20,5	21,5	5	2Q721L	
400	21,0	27,5	38,5	70	138,5	10,4	55,0	23,5	21,5	5	2R721L	
500	21,0	31,0	42,0	70	148,5	10,5	60,0	23,5	21,5	5	2S721L	
630	21,0	34,5	44,0	80	158,5	9,3	63,0	23,5	21,5	5	2T721L	